




## To Change or Add New Telephone Numbers

Display will read 'READY and display the time' or 'READY MEMORY'

1. Press >> twice, the display will read 'USER SETTING'.
2. Press the 'OK' button, the display will read 'ENTER CODE \*\*\*\*' once the code has been entered, the display will read 'SET BYPASS'.
3. Press the '>>' button three times, the display will read 'PRIVATE REPORT'.
4. Press the 'OK' button the display will read 'VOICE REPORT'.
5. Press the 'OK' button, the display will read 'REPORTED EVENTS'.
6. Press the '>>' button, the display will read '1<sup>ST</sup> PRIVATE TEL'.
7. Press the 'OK' button, the display will read '\_\_\_\_\_ ' (Tel No. programmed in).
8. Type in new number.
9. Press the 'OK' button twice, the display will read '1<sup>ST</sup> PRIVATE TEL'.
10. Press >> to select 2<sup>nd</sup>, 3<sup>rd</sup> or 4<sup>th</sup> Private Tel. and follow steps 7 to 9 again.
11. Press 'AWAY'  button, the display will read 'OK' TO EXIT'.
12. Press the 'OK' button, the display will read 'READY and display the time'.  
The alarm panel will say 'Disarm, ready to arm'.

## To Delete Telephone Numbers

Display will read 'READY and display the time' or 'READY MEMORY'

1. Press >> twice, the display will read 'USER SETTING'.
2. Press the 'OK' button, the display will read 'ENTER CODE \*\*\*\*' once the code has been entered, the display will read 'SET BYPASS'.
3. Press the '>>' button three times, the display will read 'PRIVATE REPORT'.
4. Press the 'OK' button the display will read 'VOICE REPORT'.
5. Press the 'OK' button, the display will read 'REPORTED EVENTS'.
6. Press the '>>' button, the display will read '1<sup>ST</sup> PRIVATE TEL'.
7. Press the 'OK' button, the display will read '\_\_\_\_\_ ' (Tel No. programmed in).
8. Press  (This will clear the telephone number).
9. Press the 'OK' button twice, the display will read '1<sup>ST</sup> PRIVATE TEL'.
10. Press >> to select 2<sup>nd</sup>, 3<sup>rd</sup> or 4<sup>th</sup> Private Tel. and follow steps 7 to 9 again.
11. Press 'AWAY'  button, the display will read 'OK' TO EXIT'.
13. Press the 'OK' button, the display will read 'READY and display the time'.  
The alarm panel will say 'Disarm, ready to arm'.